SPA-1003-27H

2-WAY SMT SPLITTER

RoHS Compliant and Pb-Free Product Package: S06

Features

- Frequency Range: 30MHz to 1000MHz
- Low Cost and RoHS Compliant
- Industry Standard SMT package
- Available in Tape-and -Reel
- 75Ω Characteristic Impedance

SPA-27H

Product Description


The SPA-1003-27H is a 0 $^{\circ}$ two way power splitter designed for applications that require small, low cost, and highly reliable surface mount components. Applications may be found in broadband, wireless, and other communications systems. These units are built Lead-Free and RoHS Compliant. S-Parameters are available on request.

Specifications


Parameter	Specification			Unit
	Min.	Тур.	Max.	Oilit
Frequency Range	30		1000	MHz
Insertion Loss		0.5	1.0	dB
Isolation	25	30		dB
Return Loss	20	25		dB
Amplitude Balance		0.2	0.4	dB
Phase Balance		2.0	4.0	۰

Note: Typical values represent midband performance at T=25 ° C.

Q OUTPUT 1



Schematic








1 of 2

SPA-1003-27H










Pin Out

Pin	Name		
1	Input		
3	Output 1		
4	Output 2		
2, 5, 6	Ground		

Absolute Maximum Ratings

Parameter	Rating	Unit
RF Power	+33	dBm
Operating Temperature	-55 to +100	°C
Storage Temperature	-55 to +100	°C

Package Drawing - S06



Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.

RoHS status based on EU Directive 2002/95/EC (at time of this document revision).

The information in this publication is believed to be accurate and reliable. However, no responsibility is assumed by MiniRF, Inc. ("MiniRF") for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of MiniRF. MiniRF reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

2 of 2